

TABLE ZS-2

PERFORMANCE CRITERIA LIMITS EXCEEDED AND OTHER CONSTRAINTS – 2013 Summer Peak, High Growth, 3000 MW Import and 90% East-to-West Bias Cases

Planning Zone	Criteria Exceeded/Need	2013 Summer Peak Case		2013 High Load Growth		2013-70% - 3000 MW Import Case		2013-90% - E-W Bias Case		Facility Outage(s)	Project
		% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage		
1	Eagle River Muni 115-kV bus voltage	-	111.4%	-	110.1%	-	104.2%	-	113.6%	Eagle River Muni – Cranberry 115-kV line	Take Lakota Road capacitor out of service
1	Arrowhead 345-kV bus voltage	-	110.5%	-	110.6%	-	111.7%	-	110.8%	Arrowhead 345/230-kV Transformer Arrowhead 230-kV PST	Place Stone Lake inductor in-service
1	Stone Lake 345-kV bus voltage	-	-	-	-	-	-	-	105.8%	Base Case	Place Stone Lake inductor in-service
1	Rocky Run 345/115-kV transformer #3	-	-	95.6 – 95.9%	-	-	-	-	-	Rocky Run 345/115-kV transformer #2 Sigel – Arpin 115-kV line	No project required as yet (pending overload under high load growth scenario)
1	Wien – Stratford 115-kV line	104.4 – 105.7%	-	95.5 – 110.9%	-	105.1%	-	95.3 – 98.2%	-	Arpin 345/138-kV transformer Arpin 138/115-kV transformer Arpin-Galvin 115-kV line Glavin-Hume 115-kV line Hume-Wildwood 115-kV line	Use recently validated circuit ratings
1	Stratford - McMillan 115-kV line	-	-	99.5%	-	-	-	-	-	Galvin-Hume 115-kV line	Use recently validated circuit ratings
1	Sigel, Lakehead Vesper and Port Edwards 138-kV bus voltages	-	90.0 – 91.0%	-	89.6 – 90.7%	-	-	-	90.9 – 91.8%	Arpin-Sigel 138-kV line	Publicly announced load curtailments
1	Vulcan, Hollywood and Saratoga 138-kV bus voltages	-	91.0 – 91.6%	-	90.7 – 91.3%	-	-	-	91.8%	Arpin-Sigel 138-kV line	Publicly announced load curtailments
1	Petenwell 138/68 kV transformer	97.0%	-	98.0%	-	-	-	-	-	North Fond du Lac – Rosendale 69-kV line	No project needed yet
1	Castle Rock – Quincy 69-kV line	101.3 – 101.4%	-	101.2-101.3%	-	-	-	-	-	Petenwell 138/69-kV transformer Petenwell-Big Pond 69-kV line Big Pond-Necedah tap 69-kV line	Uprate Castle Rock-McKenna 69-kV circuit
1	McKenna – Quincy 69-kV line	95.8%	-	95.4%	-	-	-	-	-	Petenwell 138/69-kV transformer Petenwell-Big Pond 69-kV line Big Pond-Necedah tap 69-kV line	Uprate Castle Rock-McKenna 69-kV circuit
1	Council Creek and Petenwell 138-kV bus voltages	-	87.4 – 94.1%	-	87.0 – 93.8%	-	-	-	89.2 – 95.8%	Base Case Saratoga-Petenwell 138-kV line Arpin-Sigel 138-kV line Sigel-Lakehead Vesper 138-kV line Hillsboro 161/69-kV transformer	Monroe County – Council Creek 161-kV line
1	Petenwell, Necedah, Whistling Wings, Dellwood, Friendship, Houghton Rock and McKenna 69-kV bus voltages	-	85.6 – 92.0%	-	84.7 – 91.5%	-	91.8 – 91.9%	-	87.7 – 91.7%	Petenwell 138/69-kV transformer Petenwell-Big Pond 69-kV line Big Pond-Necedah tap 69-kV line Necedah tap-Whistling Wings tap 69-kV line	McKenna capacitor bank expansion
1	Metomen 138/69-kV transformer	-	-	95.2 – 102.6%	-	-	-	-	-	Metomen-Rosendale 69-kV line Rosendale-North Fond du Lac 69-kV line Winneconne-Sunset Point 69-kV line North Randolph-Markesan tap 69-kV line	Metomen transformer replacement
1	Coloma(ACEC), Lincoln Pumping Station, Brooks and Grand Marsh 69 kV bus voltages	-	92.0%	-	91.4 – 92.0%	-	-	-	-	Chafee Creek-Coloma tap 69-kV line Lincoln PS-Coloma tap 69-kV line	McKenna capacitor bank expansion
2	Delta – Mead 69-kV line	103%-164%	-	108-173%	-	95-112%	-	107-146%	-	Base Case Chandler-Lakehead Tap 69-kV line Lakehead Tap-Masonville 69-kV line Masonville-Gladstone 69-kV line Gladstone-North Bluff 69-kV line North Bluff-Bay Tap 69-kV line Bay Tap-Mead 69-kV line	Uprate Delta-Mead-North Bluff 69-kV line, or dispatch local generation
2	Chandler – Delta 69-kV #1 line	111%	-	120%	-	120%	-	-	-	Chandler-Delta 69-kV #2 line	Uprate Chandler-Delta 69-kV line #1, or dispatch local generation
2	Chandler – Delta 69-kV #2 line	105%	-	114%	-	114%	-	-	-	Chandler-Delta 69-kV #1 line	Uprate Chandler-Delta 69-kV line #2, or dispatch local generation
2	Chandler 138/69-kV transformer	95-104%	-	98-109%	-	95-104%	-	-	-	Nordic-Mountain 69 kV Mountain-Harris Tap 69-kV line Forsyth 138/69-kV transformer	Increased existing summer emergency rating from SELD
2	Chandler – Lakehead Tap 69-kV line Masonville – Lakehead Tap 69-kV line Masonville – Gladstone 69-kV line Gladstone – North Bluff 69-kV line North Bluff – Bay Tap 69-kV line Mead – Bay Tap 69-kV line	128-163%	-	133-173%	-	98-109%	-	110-144%	-	Delta-Mead 69-kV line	Uprate Chandler-Masonville, Masonville-Gladstone, Gladstone-North Bluff, Delta-Mead-North Bluff 69-kV lines; or dispatch local generation
2	Pine River-Straits 69-kV line	-	-	-	-	-	-	96%	-	Straits-Brevort 138-kV line	Dispatch of hydro and/or diesel generation
2	Forsyth 138/69-kV transformer	-	-	97%	-	-	-	-	-	Chandler 138/69-kV transformer	Uprate the Forsyth 138/69-kV transformer

TABLE ZS-2 (continued)

PERFORMANCE CRITERIA LIMITS EXCEEDED AND OTHER CONSTRAINTS – 2013 Summer Peak, High Growth, 3000 MW Import and 90% East-to-West Bias Cases

Planning Zone	Criteria Exceeded/Need	2013 Summer Peak Case		2013 High Load Growth		2013-70% - 3000 MW Import Case		2013-90% - E-W Bias Case		Facility Outage(s)	Project
		% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage		
2	Ontonagon-UPPSCO Tap 69-kV line Line, Ontonagon 138/69-kV transformer	-	-	-	-	-	-	97-100%	-	Mass-Rockland 69-kV line Rockland-Rockland Junction 2 69-kV line Rockland Junction 2-Victoria 69-kV line	Dispatch local generation
2	Indian Lake 138/69-kV transformers 1, 2	-	-	-	-	-	-	102%	-	Indian Lake 138/69-kV transformer 1, 2	Operating guide
2	Lakota Road 115-kV bus voltage Engadine, Straits, Hiawatha 69-kV bus voltages	-	105.0-105.2%	-	105.0%	-	-	-	-	Base Case	Operating guide
2	Lakota Road 115-kV bus voltage Indian Lake, Perkins, Atlantic 138-kV bus voltages, Munising, Alger 69-kV bus voltages	-	-	-	-	-	105.1-106.0%	-	-	Base Case	Operating guide
2	Lakota Road 115-kV bus voltage	-	-	-	-	-	-	-	105.1%	Base Case	Operating guide
2	Delta, West Side, Escanaba, Masonville, Mead, Gladstone, Bay View, North Bluff, Harris 69-kV bus voltages	-	91.7%-92.0%	-	90.4-92.0%	-	90.9-91.8%	-	-	Chandler 138/69-kV transformer	North Bluff 69-kV capacitor bank, or dispatch local generation
2	Atlantic 138-kV bus voltage	-	88.4%	-	86.8%	-	115.1%	-	-	Atlantic-M-38 138-kV line	M38 138-kV capacitor bank
2	Engadine, Newberry Village, Lou Pac, Newberry, Newberry Hospital, Newberry Hospital Tap, Roberts, Hulbert, Eckerman, Raco 69-kV bus voltages	-	-	-	-	Eastern U.P. Votlage Collapse	-	-	-	Hiawatha-Engadine 69-kV line Engadine-Newberry 69-kV line	9 Mile/Roberts 69-kV capacitor banks, and/or dispatch local generation
2	Engadine, Newberry Village, Lou Pac, Newberry, Newberry Hospital, Newberry Hospital Tap, Roberts, Hulbert, Eckerman, Raco 69-kV bus voltages	-	-	-	-	-	-	-	Eastern U.P. Votlage Collapse	Hiawatha-Engadine 69-kV line	9 Mile/Roberts 69-kV capacitor banks, and/or dispatch local generation
2	Engadine, Newberry Village, Lou Pac, Newberry, Newberry Hospital, Newberry Hospital Tap, Roberts, Hulbert, Eckerman, Raco 69-kV bus voltages	-	-	-	-	-	-	-	86.4-91.0%	Engadine-Newberry 69-kV line	9 Mile/Roberts 69-kV capacitor banks, and/or dispatch local generation
2	L'Anse 69-kV bus voltage	-	-	-	91.6%	-	-	-	-	M38 138/69-kV transformer	L'Anse 69-kV capacitor bank
3	North Stoughton-Stoughton East- Stoughton 69-kV line	131.9%-110.7%	-	143.3%-98.3%	-	-	-	115.7%-97.6%	-	McCue-Harmony 69-kV line Harmony-Lamar 69-kV line	Rebuild Stoughton Substation bus
3	Sheepskin-Dana Tap 69-kV line	110.2%-105%	-	120.5%-114.4%	-	-	-	-	-	McCue-Harmony 69-kV line Harmony-Lamar 69-kV line	Sheepskin Substation protection project
3	Enzyme Bio Systems-RC3 69-kV line	109.6%-96.1%	-	114.1%-96.6%	-	-	-	109.4%-95.7%	-	Colley Road-Dickinson 138-kV line Dickinson-Global Renewable Energy 138-kV line Brick Church 138/69-kV transformer Global Renewable Energy-Brick Church 138-kV line	Rebuild Y-32 Colley Road-Brick Church 69-kV line
3	Stoughton-Sheepskin 69-kV line	107.4%-102.8%	-	118.1%-112.6%	-	-	-	-	-	McCue-Harmony 69-kV line Harmony-Lamar 69-kV line	Install a 138/69-kV transformer at Bass Creek Substation and rebuild/reconductor X-12 Town Line Road-Bass Creek 138-kV line
3	North Lake Geneva-Lake Geneva 69-kV line	105.7%	-	111.1%-96.6%	-	-	-	-	-	Brick Church-Cobble Stone 69-kV line	Uprate Y-152 North Lake Geneva-Lake Geneva 69-kV line to achieve a 115 MVA summer emergency rating
3	Fitchburg-Syene 69-kV line	105.5%	-	110.9%	-	-	-	95.7%	-	Royster-Pflaum Tap 69-kV line	Loop 6947 Nine Springs-Pflaum 69-kV line into Femrite Substation
3	Academy-Columbus Muni 2 Tap 69-kV line and Columbus Muni 2 Tap- Columbus 69-kV line	103.2%-98%	-	105-100.8%	-	-	-	100.6%-97.1%	-	N Randolph-Fox Lake 138-kV line Fox Lake-N Beaver Dam 138-kV line	Construct a Horicon-East Beaver Dam 138-kV line
3	McCue-Harmony-Lamar 69-kV line	102.5%-96.8%	-	108%-95.2%	-	-	-	-	-	Kegonsa 138/69-kV transformer Kegonsa-N Stoughton 69-kV line	Uprate Y-61 McCue-Lamar 69-kV line to achieve 300 deg F line ratings and install 2-12.45 Mvar 69 kV capacitor banks at Lamar Substation
3	Royster-Pflaum Tap 69-kV line	102.4%	-	107.4%	-	-	-	-	-	Fitchburg-Syene 69-kV line	Loop 6947 Nine Springs-Pflaum 69-kV line into Femrite Substation
3	Colley Road-Marine 138-kV line	98.6%	-	101.3%-95.5%	-	-	-	-	-	Paddock-NW Beloit 138-kV line	Colley Road protection project in 2010
3	McCue-Milton Lawn 69-kV line	97.7%	-	102.6%	-	-	-	-	-	Janesville 138/69-kV transformer	Uprate terminal limitations at McCue for the Y-79 McCue-Milton Lawns 69-kV line
3	N Monroe-Idle Hour 69-kV line	97.6%-95.3%	-	102.1%-95.4%	-	-	-	-	-	Darlington-Gratiot 69-kV line Gratiot-Wiota 69-kV line	Install a 138/69-kV transformer at Bass Creek Substation and rebuild/reconductor X-12 Town Line Road-Bass Creek 138-kV line and Rebuild Y-33 Brodhead to South Monroe 69-kV line

TABLE ZS-2 (continued)

PERFORMANCE CRITERIA LIMITS EXCEEDED AND OTHER CONSTRAINTS – 2013 Summer Peak, High Growth, 3000 MW Import and 90% East-to-West Bias Cases

Planning Zone	Criteria Exceeded/Need	2013 Summer Peak Case		2013 High Load Growth		2013-70% - 3000 MW Import Case		2013-90% - E-W Bias Case		Facility Outage(s)	Project
		% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage		
3	Walworth-Schofield 69-kV line	97.1%	-	101.5%	-	-	-	-	-	N Lake Geneva-138/69-kV transformer	Uprate Y-41 Walworth- North Lake Geneva 69-kV to achieve a 69 MVA summer emergency rating
3	Gran Grae-Wauzeka-Boscobel 69-kV line	97.1%-96.8%	-	100.9%-96%	-	-	-	-	-	Spring Green 138/69-kV transformer Nelson Dewey-Lancaster 138-kV line Spring Green-Lone Rock 69-kV line	Uprate Y-40 Gran Grae-Boscobel 69-kV line to achieve a 99 MVA summer emergency rating
3	Rock Springs Tap – Artesian 138-kV line	96.7%-95.8%	-	98.2%-95.7%	-	-	-	-	-	Trienda-Lewiston 138-kV line East Dells-Lewiston 138-kV line	Construct a Lake Delton-Birchwood 138-kV line
3	Colley Road 138/69-kV transformer	96.4%	-	100.1%	-	-	-	-	-	Paddock 138/69-kV transformer	Install a 138/69-kV transformer at Bass Creek Substation and rebuild/reconductor X-12 Town Line Road-Bass Creek 138-kV line
3	Dane-Lodi Tap 69-kV line	95.7%	-	99.9%	-	-	-	-	-	Kirkwood-Island 69-kV line	Rebuild part of the Y-8 Dane-Dam Heights 69-kV line
3	Shaw-Shirland Ave 69-kV line	95.2%	-	98.8%	-	-	-	-	-	Colley Road 138/69-kV transformer	Rating increase after SELD validation
3	Jefferson, Lake Mills, Fort Atkinson, Crawfish, Concord, Rubicon, Hustisford, Hubbard and Butler Ridge 138-kV buses	-	91.4%-95.8%	-	90.8%-95.1%	-	-	-	93.1%-95.9%	Base Case	Install 4-49 MVAR 138-kV capacitor banks at Concord Substation
3	Brick Church 138-kV bus	-	95.6%	-	-	-	-	-	-	Base Case	Install 2-24.5 Mvar 138-kV capacitor banks and 1-18 Mvar 69-kV capacitor bank at Brick Church substation
3	Harmony, Lamar, Fulton, Saunders Creek, Dana Corp, Sheepskin and Evansville 69-kV buses	-	78.7%-91.8%	-	75.3%-92%	-	88.8%-91.8%	-	83.9%-91.9%	McCue-Harmony 69-kV line Harmony-Lamar 69-kV line Lamar-Fulton 69-kV line	Uprate Y-61 McCue-Lamar 69-kV line to achieve 300 deg F line ratings and install 2-12.45 Mvar 69-kV capacitor banks at Lamar Substation and Install a 138/69-kV transformer at Bass Creek Substation and rebuild/reconductor X-12 Town Line Road-Bass Creek 138-kV line
3	Lakehead Cambridge Tap, Fort Atkinson, Jefferson, Crawfish, Concord ,Hubbard, Hustisford, Rubicon and Butler Ridge 138-kV buses	-	83.6%-91.3%	-	87.1%-91.9%	-	91.4%-91.8%	-	86.4%-91.8%	Rockdale to Lakehead Cambridge Tap 138-kV line Lakehead Cambridge Tap-Jefferson4 138-kV line Jefferson4-Jefferson 5 Bus outage Jefferson5-Crawfish 138-kV line Crawfish-Concord4 138-kV line Plus other less severe outages	Install 4-49 MVAR 138-kV capacitor banks at Concord Substation
3	Spring Green, Arena, Mazomanie, Mazomanie Industrial, Lone Rock, Muscodia, Avoca, Blue River, Boscobel, Boscobel Muni 69-kV bus voltages	-	85.9%-91.4%	-	84.5%-91.8%	-	-	-	89.1%-91.8%	Spring Green 138/69-kV transformer	Install 2-16.33 MVAR 69-kV capacitor banks at Spring Green Substation and Install a second 138/69-kV transformer at Spring Green with a 100 MVA summer normal rating
3	Brodhead Muni 3, Brodhead Muni 2, Brodhead, Brodhead Muni 1, RCEC Orfordville, Orfordville, Bass Creek, Footville, RCEC Center, Evansville 69-kV bus voltages	-	86%-92%	-	84.2%-91.3%	-	-	-	89.2%-91.5%	Brodhead Switching Sta-Brodhead Muni 3 69-kV line Brodhead Muni 2 -Brodhead Muni 3 69-kV line Brodhead Muni 2-Brodhead 69-kV line	Install a 138/69-kV transformer at Bass Creek Substation and rebuild/reconductor X-12 Town Line Road-Bass Creek 138-kV line
3	Dickinson, Global Renewable Energy, William Bay and Brick Church 138-kV buses	-	87.1%-91.5%	-	86.1%-91.8%	-	87.1%-91.7%	-	86.6%-91.9%	Colley Road – Dickinson 138-kV line Dickinson-Global Renewable Energy 138-kV line Global Renewable Energy-Brick Church 138-kV line	Install 2-24.5 Mvar 138-kV capacitor bank and 1-18 Mvar 69-kV capacitor bank at Brick Church Substation
3	Hubbard and Hustisford 138-kV buses	-	88.5%-89.1%	-	88.1%-88.8%	-	88.3%-88.6%	-	88.3%-88.8%	Rubicon-Hustisford 138-kV line Hubbard-Hustisford 138-kV line	Construct a Horicon-East Beaver Dam 138-kV line
3	Evansville 69-kV bus	-	90.6%	-	89.5%-91.9%	-	-	-	-	Evansville-Sheepskin 69-kV line	Install a 138/69-kV transformer at Bass Creek Substation and rebuild/reconductor X-12 Town Line Road-Bass Creek 138-kV line
3	Lake Geneva and Twin Lake 69-kV buses	-	91.9%-92%	-	89.6%-90.6%	-	-	-	-	N Lake Geneva-Lake Geneva 69-kV line	Construct new 138-kV line from North Lake Geneva to South Lake Geneva Substation and construct new 138-kV bus and install a 138/69-kV 100 MVA transformer at South Lake Geneva Substation
3	Eden, Wyoming Valley and Lancaster 138-kV buses	-	89.7%-91.6%	-	89%-91.8%	-	-	-	91.2%-91.9%	Nelson Dewey-Lancaster 138-kV line Lancaster-Eden 138-kV line	Install 2-16.33 MVAR 69-kV capacitor banks at Spring Green Substation and Install a second 138/69-kV transformer at Spring Green with a 100 MVA summer normal rating

TABLE ZS-2 (continued)

PERFORMANCE CRITERIA LIMITS EXCEEDED AND OTHER CONSTRAINTS – 2013 Summer Peak, High Growth, 3000 MW Import and 90% East-to-West Bias Cases

Planning Zone	Criteria Exceeded/Need	2013 Summer Peak Case		2013 High Load Growth		2013-70% - 3000 MW Import Case		2013-90% - E-W Bias Case		Facility Outage(s)	Project
		% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage		
3	Lone Rock, Muscoda, Avoca, Blue River, Boscobel, Boscobel Muni 69-kV bus voltages	-	89.7%-91.9%	-	88.7%-91%	-	-	-	91.9%	Lone Rock-Spring Green 69-kV line	Install 1-8.16 MVAR capacitor bank at Boscobel 69-kV Substation and upgrade existing 5.4 MVAR bank with an 8.16 MVAR bank
3	Cobblestone and Zenda 69-kV buses	-	90.5%-91.7%	-	90.2%-91.6%	-	-	-	-	Brick Church-Cobblestone 69-kV line	North Lake Geneva-South Lake Geneva 138-kV line project in 2014. The need year is determined by Cobblestone voltage problem.
3	Idle Hour, Monroe and S Monroe 69-kV buses	-	91.6%-92%	-	90.3%-90.7%	-	-	-	-	N Monroe-Idle Hour 69-kV line	Rebuild Y-33 Brodhead to South Monroe 69-kV line
3	Avoca, Muscoda 69-kV buses	-	91.9%	-	90.2-91.4%	-	-	-	-	Lone Rock-Avoca 69-kV line	Install 1-8.16 MVAR capacitor bank at Boscobel 69-kV Substation and upgrade existing 5.4 MVAR bank with an 8.16 MVAR bank
3	Troy 138-kV bus	-	92%	-	91.2%-91.9%	-	-	-	-	Kirkwood-Troy 138-kV line Troy-Spring Green 138-kV line	Install 2-16.33 MVAR 69-kV capacitor banks at Spring Green Substation and Install a second 138/69-kV transformer at Spring Green with a 100 MVA summer normal rating
3	Burke and Reiner 69-kV buses	-	-	-	90.9%-91.6%	--	92%	-	-	Reiner Road 138/69-kV transformer	Install 2-16.33 Mvar 69-kV capacitor banks at Sun Prairie
3	West Middleton-Black Hawk 69-kV line	-	-	-	-	101.6%	-	-	-	Base Case	Dispatch local generation
3	Nelson Dewey 161/138-kV transformer	-	-	-	-	115.3%	-	-	-	Base Case	2 nd Nelson Dewey 161/138 kV transformer
3	Paddock 345/138-kV transformer	-	-	-	-	97.1%	-	-	-	Base Case	Dispatch local generation
3	Benton-Miner 69-kV line	-	-	-	-	109%	-	-	-	Nelson Dewey 161/138-kV transformer	2 nd Nelson Dewey 161/138 kV transformer
3	Paddock-NW Beloit-Blackhawk 138-kV line	-	-	-	-	100.7%-98%	-	-	-	Paddock-Townline 138-kV line	Dispatch local generation
3	North Stoughton-Stoughton East-Stoughton 69-kV line	-	-	-	-	118.5%-107.4%	-	-	-	Paddock 345/138 kV transformer and Paddock-Wempletown 345-kV lines	Dispatch local generation
3	West Middleton-Black Hawk 69-kV line	-	-	-	-	108.4%-95%	-	-	-	North Madison-Vienna 138-kV line Vienna-Yahara 138-kV line Yahara-American Center 138-kV line Kegonsa-McFarland 138-kV line McFarland-Femrite 138-kV line Plus other less severe outages	Dispatch local generation
3	Nelson Dewey 161/138-kV transformer	-	-	-	-	100.6%-96.5%	-	-	-	Paddock 345/138-kV transformer Paddock-Wempletown 345-kV line Rockdale-Wempletown 345-kV line Byron-Wempletown 345-kV line	2 nd Nelson Dewey 161/138-kV transformer
3	North Monroe-Darlington 138-kV line	-	-	-	-	103.7%	-	-	-	Paddock 345/138 kV transformer	Dispatch local generation
3	Paddock-Townline 138-kV line	-	-	-	-	105.2%-96.1%	-	-	-	Paddock-NW Beloit 138-kV line NW Beloit-Blackhawk 138-kV line Blackhawk-Colley Road 138-kV line	Dispatch local generation
3	Entire Rock County and Walworth County 138-kV bus voltages	-	-	-	-	-	92.5%-96%	-	-	Base Case	Dispatch local generation
3	Fitchburg, Oakridge 138-kV buses	-	-	-	95.5%	-	95.8%-95.9%	-	-	Base Case	Dispatch local generation
3	Concord 138-kV buses	-	-	-	-	-	95.4%	-	-	Base Case	Install 4-49 MVAR 138-kV capacitor banks at Concord Substation
3	Entire Rock County and Walworth County 138-kV bus voltages	-	-	-	-	-	82.7%-92%	-	-	Paddock 345/138 kV transformer Paddock-Wempletown 345-kV line Rockdale-Wempletown 345-kV line Byron-Wempletown 345-kV line	Dispatch local generation
3	Entire Rock County and Walworth County 138-kV bus voltages	-	-	-	-	-	87.7%-92%	-	-	Burlington 138-kV bus 1-2 outage Burlington-Air Liquide 138-kV line Air Liquide-Paris 138-kV line	Dispatch local generation
3	Williams Bay 138-kV bus	-	-	-	-	-	90.7%	-	-	Elkhorn-Williams Bay 138-kV line	Dispatch local generation
3	La Prairie, Bradford, West Darien, SW Delavan and North Shore 138-kV buses	-	-	-	91.7%-91.9%	-	91.8%	-	-	Rock River-La Prairie 138-kV line La Prairie-Bradford 138-kV line Bradford-West Darien 138-kV line	Dispatch local generation
3	Sugar Creek 138-kV bus	-	-	-	-	-	91.9%	-	-	Burlington-N Lake Geneva Tap 138-kV line	Dispatch local generation
3	Brick Church, Williams Bay, Elkhorn and North Lake Geneva 138-kV buses	-	-	-	-	-	90.8%-91.8%	-	-	North Lake Geneva Tap-North Lake Geneva 138-kV line	Dispatch local generation
3	North Lake Geneva Tap 138-kV bus voltage	-	-	-	-	-	-	-	92%	Burlington 138-kV bus 1-2 outage	Dispatch local generation
3	Whitewater 138-kV bus	-	-	-	-	-	-	-	91.7%	Whitewater 138-kV bus 4-5 outage Whitewater-Lakehead Tap 138-kV line	Dispatch local generation
3	Whitewater, Lakehead, University and Bluff Creek 138-kV buses	-	-	-	-	-	-	-	90.7%-91.9%	Sunrise-Lakehead Tap 138-kV line	Dispatch local generation

TABLE ZS-2 (continued)

PERFORMANCE CRITERIA LIMITS EXCEEDED AND OTHER CONSTRAINTS – 2013 Summer Peak, High Growth, 3000 MW Import and 90% East-to-West Bias Cases

Planning Zone	Criteria Exceeded/Need	2013 Summer Peak Case		2013 High Load Growth		2013-70% - 3000 MW Import Case		2013-90% - E-W Bias Case		Facility Outage(s)	Project
		% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage		
3	Spring Green and Wyoming Valley 138-kV buses	-	-	-	95.9%	-	-	-	-	Base Case	Install 2-16.33 MVAR 69-kV capacitor banks at Spring Green Substation and install a second 138/69-kV transformer at Spring Green with a 100 MVA summer normal rating
3	Cobblestone- Zenda 69-kV line	-	-	95.5%	-	-	-	-	-	North Lake Geneva-Lake Geneva 69-kV line	Construct new 138-kV line from North Lake Geneva to South Lake Geneva Substation and construct new 138-kV bus and install a 138/69-kV 100 MVA transformer at South Lake Geneva Substation
3	Spring Green 138/69-kV transformer	-	-	99.5%-97.4%	-	-	-	-	-	Gran Grae-Wauzeka 69-kV line Wauzeka-Boscobel 69-kV line	Install 2-16.33 MVAR 69-kV capacitor banks at Spring Green Substation and install a second 138/69-kV transformer at Spring Green with a 100 MVA summer normal rating
3	Stage Coach-Black Earth 69-kV line	-	-	97%	-	-	-	-	-	Spring Green 138/69-kV transformer	Install 2-16.33 MVAR 69-kV capacitor banks at Spring Green Substation and install a second 138/69-kV transformer at Spring Green with a 100 MVA summer normal rating
3	Nine Springs-Syene 69-kV line	-	-	97%	-	-	-	-	-	Royster-Pflaum 69-kV line	Loop 6947 Nine Springs-Pflaum 69-kV line into Femrite Substation
3	South Fond Du Lac-Waupun 69-kV line	-	-	103.6%-102.5%	-	-	-	-	-	North Randolph-Fox Lake 138-kV line Fox Lake-N Beaver Dam 138-kV line	Construct a Horicon-East Beaver Dam 138-kV line
3	Bluff Creek and Sugar Creek 138-kV buses	-	-	91.3%-91.7%	-	-	-	-	-	University-Bluff Creek 138-kV line	Dispatch local generation
3	Brodhead Muni 3, Brodhead Muni 2, Brodhead, Brodhead Muni 1, RCEC Orfordville, Orfordville, Bass Creek, Footville, RCEC Center, Evansville 69-kV bus voltages	-	-	91.1%-92%	-	-	-	-	-	Paddock-Newark 69-kV line	Install a 138/69-kV transformer at Bass Creek Substation and rebuild/reconductor X-12 Town Line Road-Bass Creek 138-kV line
3	Rockdale-Lakehead Cambridge 138-kV line	95.2%	--	--	--	--	--	--	--	Oak Creek generation unit 1 or 2	Construct new 138-kV line from North Lake Geneva to South Lake Geneva Substation and construct new 138-kV bus and install a 138/69-kV 100 MVA transformer at South Lake Geneva Substation Construct Spring Valley-Twin Lakes-South Lake Geneva 138-kV line
4	Pulliam-Suamico 69-kV line	100.8%	-	105.6%	-	-	-	-	-	Base case	Rebuild/Convert Bayport-Suamico-Sobieski-Pioneer 69-kV line to 138 kV
4	West Marinette 138/69-kV transformer #1	97.8-96.3%	-	100-101.9%	-	-	-	-	-	Wells St-Roosevelt 69-kV line Roosevelt 138/69-kV transformer	Expand the Menominee 69-kV Substation and install 138 kV terminals. Loop the West Marinette-Bay De Noc 138-kV line into the Substation Install 138/69-kV transformer at the expanded Menominee Substation
4	Pioneer-Sobieski 69-kV line	110.3%	-	116.5%	-	-	-	99.4%	-	Pulliam-Suamico 69-kV line followed by Sobieski-Pioneer 69-kV line close	Rebuild/Convert Bayport-Suamico-Sobieski-Pioneer 69-kV line to 138 kV
4	Sunset Point-Pearl Ave 69-kV line	104.4%	-	109.5%	-	-	-	-	-	Ellinwood-Twelfth Avenue 69-kV line	Rebuild 2.37 miles of 69 kV from Sunset Point to Pearl Ave with 477 ACSR
4	Melissa-Tayco 138-kV line	103.8%	-	-	-	-	-	-	-	Butte Des Morts 138-kV bus tie 1-2 outage	Uprate the Melissa-Tayco to 229 MVA (300F)
4	North Appleton-Fox River 345-kV line	-	-	-	-	-	-	95.6%	-	North Appleton-Kewaunee 345-kV line	Uprate North Appleton-Fox River 345-kV line
4	Sobieski, Suamico 69-kV bus voltages	-	94.2-92.2%	-	94.3-92.2%	-	-	-	95.7-93.9%	Base case	Rebuild/Convert Bayport-Suamico-Sobieski-Pioneer 69-kV line to 138 kV
4	Sobieski 69-kV bus voltage	-	91.8%	-	-	-	-	-	-	Morgan-Highway 22 345-kV line	Rebuild/Convert Bayport-Suamico-Sobieski-Pioneer 69-kV line to 138 kV
4	Bluestone, Wesmark 69-kV bus voltages	-	90.1-87.6%	-	86.4-88.9%	-	-	-	90.3%	Finger Rd-Bluestone 69-kV line	Construct a new 138-kV substation and loop Highway V-East Krok 138-kV line into the substation
4	East Krok, Beardsley St 69-kV bus voltages	-	91.9-91.5%	-	90.8-91.2%	-	-	-	-	East Krok 138/69-kV transformer	No provisional project Additional study is being conducted.
4	Hickory, Forward Energy Center, Butternut 4, and Butternut 5 138-kV bus voltages	-	91.9%	-	91%	-	-	-	-	Hickory-South Fond du Lac 138-kV line	Install 28.8 MVAR capacitor bank at Butternut 138-kV Substation
4	Holland 138-kV bus voltage	-	91.8%	-	91.4%	-	-	-	-	Charter Steel Industry-Holland 138-kV line	No provisional project. Additional study is being conducted.
4	Suamico 69-kV bus	-	90.7%	-	89.8%	-	-	-	91.5	Pulliam-Suamico 69-kV line followed by Sobieski-Pioneer 69-kV line close	Rebuild/Convert Bayport-Suamico-Sobieski-Pioneer 69-kV line to 138 kV

TABLE ZS-2 (continued)

PERFORMANCE CRITERIA LIMITS EXCEEDED AND OTHER CONSTRAINTS – 2013 Summer Peak, High Growth, 3000 MW Import and 90% East-to-West Bias Cases

Planning Zone	Criteria Exceeded/Need	2013 Summer Peak Case		2013 High Load Growth		2013-70% - 3000 MW Import Case		2013-90% - E-W Bias Case		Facility Outage(s)	Project
		% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage		
4	Edgewater-Washington Ave 69-kV line	-	-	95.6%		-	-	-	-	Edgewater-Nicolet 69-kV line	No provisional project. Additional study is being conducted.
4	City Limits-Combined Locks Tap 138-kV line	-	-	98.1%		-	-	-	-	North Appleton-Apple Hills 138-kV line	No provisional project. Additional study is being conducted.
4	Barnett 69-kV bus voltage	-	-	-	91.8%	-	-	-	-	East Krok 138/69-kV transformer	No provisional project. Additional study is being conducted.
4	Auburn 138-kV bus voltage	-	-	-	91.7%	-	-	-	-	Hickory-South Fond du Lac 138-kV line	Install 28.8 MVAR capacitor bank at Butternut 138-kV Substation
4	Forward Energy Center, Butternut 4, and Butternut 5 138-kV bus voltages	-	-	-	91.6%	-	-	-	-	Hickory-Forward Energy Center 138-kV line	Install 28.8 MVAR capacitor bank at Butternut 138-kV Substation
4	Butternut 4, Butternut 5 138-kV bus voltages	-	-	-	91.8%	-	-	-	-	Butternut 5-Forward Energy Center 138-kV line	Install 28.8 MVAR capacitor bank at Butternut 138-kV Substation
4	Holland 138-kV bus voltage	-	-	-	91.9%	-	-	-	-	Charter Steel Industry 138-kV bus plus Charter Steel-Cedarsauk 138-kV line	No provisional project. Additional study is being conducted.
5	Concord 138-kV bus voltage Allerton 138-kV bus voltage Bark River 138-kV bus voltage Brookdale (East) 138-kV bus voltage Edgewood 138-kV bus voltage Cooney 138-kV bus voltage Cottonwood 138-kV bus voltage Germantown 138-kV bus voltage Hartford 138-kV bus voltage Merrill Hills 138-kV bus voltage Mukwonago 138-kV bus voltage Maple 138-kV bus voltage Pleasant Valley 138-kV bus voltage St. Lawrence 138-kV bus voltage Summit 138-kV bus voltage Sussex 138-kV bus voltage Arthur Road 138-kV bus voltage Glacier 138-kV bus voltage Albers – Paris 138-kV line	--	90.6% 94.7% 91.8% > 96.0% 94.4% 90.0% 90.5% 91.7% 92.6% 92.7% 93.8% 92.3% > 95.0% 94.0% 90.2% 94.9% 94.0% 94.5%		89.9% 93.9% 91.9% 94.6% 93.7% 89.4% 90.3% 93.6% 92.0% 92.1% 93.2% 93.9% 94.6% 93.5% 89.7% 94.6% 93.5% 94.2%				94.1% --- 94.9% --- --- 93.4% 93.9% 94.7% --- 94.9% --- --- --- --- 93.5% --- --- ---	Intact System (No Concord or Germantown generation is on line in the summer peak model. One Germantown unit is on line in the high load growth model. Voltages are based on 90% machine Q. Contingencies based on 95% Q) * Two 32 MVar capacitors were placed in service at Summit prior to 2013 summer peak contingency analysis and high load growth contingency analysis. Intact system voltages are prior to capacitor installation.	Dispatch local generation
5	Concord, Cooney, Cottonwood, Summit, Bark River 138-kV bus voltages	--	86.6 – 89.8% 87.2 – 89.7% 86.8 – 89.6% 87.4 – 89.4% 88.7 – 89.9% --	--	85.6 – 89.4% 84.7 – 87.9% 87.5 – 89.2% 86.1 – 89.5% % 87.2 – 88.6% --	--	--	--	89.8 % -- -- -- -- --	Jefferson-Crawfish River - Concord 138-kV line Bark River – Cottonwood 138-kV line Bark River – Sussex 138-kV line Hartford – St. Lawrence 138-kV line Cooney – Summit 138-kV line Plus other less severe outages	Summit, Mukwonago caps & Dispatch local generation
5	Germantown and Maple 138-kV bus voltages	--	88.1 – 89.2% 87.3% 82.2 – 82.5%	--	-- 88.8 – 89.2% %	--	--	--	-- 87.6 87.9%	Bark River – Sussex 138-kV line Germantown – Maple 138-kV line Maple – Saukville 138-kV line	Dispatch local generation
5	Hartford 138-kV bus voltage	--	83.9% 89.3%	--	82.3 % 88.3 %	--	--	--	89.1 % --	Hartford – St. Lawrence 138-kV line Pleasant Valley – Saukville 138-kV line	Load shifting
5	St. Lawrence, Arthur Road 138-kV bus voltage	--	--	--	89.1%	--	--	--	--	Pleasant Valley – Saukville 138-kV line	No Project Yet Load shifting
5	Pleasant Valley 138-kV bus voltage	--	89.4%	--	--	--	--	--	--	Pleasant Valley – Saukville 138-kV line	Load Shifting
5	Bain 345/138-kV transformer T5	159.9% 99.6% 100.4%	--	160.3% 98.8% 103.9%	--	139.2% -- --	--	159.1% -- 97.0%	--	Pleasant Prairie bus split between 3 and 4 Pleasant Prairie bus split between 2 and 3 Pleasant Prairie - Bain transformer T4	Dispatch local generation
5	Bain 345/138-kV transformer T4	99.6%	--	103.1%	--	--	--	96.2%	--	Pleasant Prairie - Bain transformer T5	Dispatch local generation
5	Albers – Bain 138-kV line	118.2%	--	121.6%	--	101.8%	--	117.5%	--	Bain – Kenosha 138-kV line	Uprate Albers – Bain 138-kV line Dispatch local generation
5	Edgewood – St. Martins 138-kV line	--	--	--	--	98.7% 103.6 % 107.3% 106.0% 101.2%	--	--- --- --- 96.5% ---	--	Split Burlington 138-kV bus Burlington – Air Liquide – Paris Paddock 345/138-kV transformer Merrill Hills – Waukesha 138-kV line Wempletown – Paddock 345-kV line	No project yet Dispatch local generation
5	Bain – Kenosha 138-kV line	95.6%	--	98.8	--	--	--	--	--	Albers – Bain 138-kV line	No project yet – Dispatch local generation

TABLE ZS-2 (continued)

PERFORMANCE CRITERIA LIMITS EXCEEDED AND OTHER CONSTRAINTS – 2013 Summer Peak, High Growth, 3000 MW Import and 90% East-to-West Bias Cases

Planning Zone	Criteria Exceeded/Need	2013 Summer Peak Case		2013 High Load Growth		2013-70% - 3000 MW Import Case		2013-90% - E-W Bias Case		Facility Outage(s)	Project
		% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage	% of Facility Rating	% of Nominal bus voltage		
5	Arcadian6 – Waukesha3 138-kV line	100.0%	--	101.7%	--	95.4%	--	107.7%	--	Arcadian4 – Waukesha1 138-kV line	Uprate Arcadian – Waukesha 138-kV line Dispatch local generation
5	Arcadian4 – Waukesha1 138-kV line	100.8%	--	102.5%	--	96.1%	--	108.5%	--	Arcadian6 – Waukesha3 138kV line	Uprate Arcadian – Waukesha 138-kV line Dispatch local generation
5	Maple – Saukville 138-kV line	100.3%	--	--	--	--	--	--	--	Bark River – Sussex 138-kV line	Dispatch local generation
5	Oak Creek – Pennsylvania 138-kV line	95.3 %	--	98.1% 99.4% 98.7% 97.3% 99.2%	--	--	--	95.1% 95.9% 95.4% --	--	Kansas – Ramsey 138-kV line Oak Creek – Nicholson 138-kV line Nicholson – Ramsey 138-kV line Norwich – Ramsey 138-kV line Oak Creek – Ramsey 138-kV line Plus other less severe outages	No Project yet Load Shifting
5	Oak Creek 345/138-kV transformer #2	--	--	97.4%	--	--	--	96.7%	--	Oak Creek 345/138-kV transformer #1	No project yet – Dispatch local generation
5	Branch – Kansas 138-kV line	--	--	97.8%	--	--	--	--	--	Oak Creek – Pennsylvania 138-kV line	No project yet - Load shifting
5	Nicholson – Ramsey 138-kV line	--	--	--	--	--	--	97.9%	--	Oak Creek – Pennsylvania 138-kV line	No project yet - Load shifting
5	Oak Creek – Ramsey 138-kV line	--	--	--	--	--	--	97.1%	--	Oak Creek – Pennsylvania 138-kV line	No project yet - Load Shifting
5	Bark River – Sussex 138-kV line	98.8%	--	--	--	--	--	--	--	Maple – Saukville 138-kV line	No project yet – Dispatch local generation
5	Harbor – Kansas 138-kV line	--	--	--	--	102.1% 98.7% 102.9% 103.2% 100.1%	--	--	--	Montana – Dewey 138-kV line Valley – Montana 138-kV line Split Dewey 138-kV bus Dewey – Norwich 138-kV line Kansas – Norwich 138-kV line Plus less severe outages	No project yet – Dispatch local generation
5	Tichigan , Burlington1 138-kV bus voltages	--	--	--	--	--	86.1-86.6%	--	89.3-90.0%	Split Burlington 138-kV bus	No project yet - Load Shifting
5	Paris – Albers 138-kV line	--	--	--	--	99.7%	--	--	--	Paddock 345/138-kV transformer	No project yet – Dispatch local generation
5	Tichigan, Burlington, Walworth, Air Liquide 138-kV buses	--	--	--	--	--	88.2-89.1%	--	--	Paddock 345/138-kV transformer	No project yet - Load shift
5	Albers-Kenosha 138-kV line	--	--	--	--	120.2%	--	--	109.0%	Albers – Bain 138-kV line	No project yet – Dispatch local generation
5	Granville 345/138-kV transformer #1	--	--	--	--	--	--	100.0% 98.5%	--	Granville-Cedarsauk 345-kV line Granville 345/138-kV T2 Granville 345-kV bus split between 2 and 3	No project yet – Dispatch local generation
5	Arcadian 345/138-kV transformer #2	94.9%	--	--	--	99.7%	--	98.2%	--	Arcadian 345/138-kV transformer #1	No project yet - Replace Arcadian transformer
5	Arcadian 345/138-kV transformer #3	111.8% --	--	101.0% 102.0%	--	117.4% --	--	113.2% 105.5% 101.3%	--	Arcadian 345/138-kV transformer #1 Arcadian 345-kV bus split between 1 and 2 Arcadian xfmr #2 and 345-kV bus outage	Replace Arcadian transformer