

Table ZS-1
2011 Limitations and Performance Criteria Exceeded

Planning Zone	Criteria Exceeded/Need	2011 Summer Peak Case		2011 90% Load Case		2011 70% Load Case		2011 Minimum Load Case		Facility Outage(s)	Project/Mitigation
		% of Facility Rating	% of Nominal Bus Voltage	% of Facility Rating	% of Nominal Bus Voltage	% of Facility Rating	% of Nominal Bus Voltage	% of Facility Rating	% of Nominal Bus Voltage		
1	Base case loading criteria exceeded	FALSE	--	FALSE	--	FALSE	--	FALSE	--	System Intact	
1	Base case voltage criteria exceeded	--	FALSE	--	FALSE	--	FALSE	--	TRUE	System Intact	
1	Dartford 69-kV bus	--	91.7%	--	--	--	--	--	--	Metomen – Ripon 69-kV line	Marginal voltage, no mitigation needed within this timeframe
1	Petenwell and Council Creek 138-kV buses	--	89.2% 89.2 – 89.8%	--	90.3 – 96.7% 90.1 – 91.2%	--	--	--	--	ACEC Badger West – Saratoga 138-kV line ACEC Badger West – Petenwell 138-kV line	Adjust Council Creek 138/69-kV transformer LTC
1	ACEC Badger West 138-kV bus	--	89.2%	--	90.3%	--	--	--	--	ACEC Badger West – Saratoga 138-kV line	Adjust Council Creek 138/69-kV transformer LTC
1	Necedah, ACEC Dellwood, Friendship, ACEC Friendship and Houghton Rock 69-kV buses	--	87.9 – 91.9% 87.9 – 91.9% 88.9 – 91.9% 90.9 – 91.4%	--	87.9 – 91.9% 88.7 – 91.5% 88.7 – 91.5% 90.0 – 91.4%	--	--	--	--	Petenwell 138/69-kV transformer Petenwell – Big Pond 69-kV line Necedah Tap – Big Pond 69-kV line Necedah Tap – Whistling Wings Tap 69-kV line	Mitigated by generation adjustments
1	Brooks Corner 69-kV bus	--	87.5%	--	88.2%	--	90.2%	--	91.5%	Whitcomb – Deer Trail 69-kV line ⁴	Adjust Brooks Corners 69/34.5-kV transformer LTC
1	Arpin 345-kV bus	--	--	--	--	--	--	--	105.4% 110.0%	System Intact Arpin – Rocky Run 345-kV line ¹	Switch Port Edwards 69-kV and McMillan 115-kV capacitors offline
1	Harrison 69-kV bus	--	--	--	--	--	--	--	106.4%	System Intact	Switch Harrison 69-kV capacitor offline
1	Caroline 115-kV bus	--	--	--	--	--	--	--	106.3%	System Intact	Switch area capacitor banks offline and adjust area transformer LTCs
1	Whitcomb 115-kV bus	--	--	--	--	--	--	--	106.0%	System Intact	Switch Birnamwood 69-kV capacitor bank offline and/or corrected Whitcomb transformer modeling
1	Petenwell 138/69-kV transformer	99.0% 95.6%	--	--	--	--	--	--	--	McKenna – Houghton Rock 69-kV line Castle Rock – Quincy ACEC 69-kV line	Mitigated by generation adjustments
1	Vulcan – Port Edwards 138-kV line #1 Vulcan – Port Edwards 138-kV line #2	123.0% 122.8%	--	123.0% 122.8%	--	123.0% 122.8%	--	123.0% 122.8%	--	Port Edwards – Vulcan Chemical 138-kV #2 line Port Edwards – Vulcan Chemical 138-kV #1 line	Change tap on free standing CT's at Port Edwards
2	Base case loading criteria exceeded	FALSE	--	FALSE	--	FALSE	--	FALSE	--	System Intact	
2	Base case voltage criteria exceeded	--	TRUE	--	TRUE	--	TRUE	--	TRUE	System Intact	
2	M38 – Atlantic 69-kV line	116.8 – 121.6%	--	105.0% 105.0% 110.9%	--	--	--	--	--	M38 – Atlantic 138-kV line Atlantic 138/69-kV transformer M38 – Atlantic 138-kV line ⁵	Mitigated by generation adjustments or uprate line
2	Nordic – Mountain 69-kV line	--	--	--	--	96.8% 98.8%	--	--	--	Plains – Arnold 138-kV line Chandler 138/69-kV transformer	Targeted for mitigation by Escanaba area reinforcements

Table ZS-1
2011 Limitations and Performance Criteria Exceeded

Planning Zone	Criteria Exceeded/Need	2011 Summer Peak Case		2011 90% Load Case		2011 70% Load Case		2011 Minimum Load Case		Facility Outage(s)	Project/Mitigation
		% of Facility Rating	% of Nominal Bus Voltage	% of Facility Rating	% of Nominal Bus Voltage	% of Facility Rating	% of Nominal Bus Voltage	% of Facility Rating	% of Nominal Bus Voltage		
2	Plains – Arnold 138-kV line	--	--	--	--	95.2%	--	--	--	Dead River 345/138-kV transformers ²	Targeted for mitigation by Escanaba area reinforcements
2	Straits – McGulpin 138-kV line 9903	97.6%	--	97.6%	--	--	--	--	--	Straits – McGulpin 138-kV line 9901	Targeted for mitigation by Eastern U.P. area reinforcements
2	Pine River – Straits 69-kV line Pine River – Evergreen 69-kV line Evergreen – Straits 69-kV line	--	--	102.4 – 108.8% 102.1 – 108.4% 107.1 – 113.8% 106.7 – 111.9% 105.7 – 111.0%	--	--	--	--	--	Straits – Hiawatha 138-kV line 9902 Straits 138/69-kV transformer Straits – Brevort 138-kV line Brevort – Lakehead 138-kV line Hiawatha – Lakehead 138-kV line	Targeted for mitigation by Eastern U.P. area reinforcements
2	Engadine, Newberry, Newberry Hospital, Roberts, LouPac, Newberry Village, Hulbert and Eckerman 69-kV buses	--	82.9 – 90.7%	--	--	--	--	--	--	Hiawatha – Engadine 69-kV line Engadine – Newberry 69-kV line	Mitigated by generation adjustments
2	Engadine, Newberry, LouPac, Newberry Hospital, Newberry Village, Roberts 69-kV buses	--	--	--	89.4 – 89.9%	--	--	--	--	Hiawatha – Engadine 69-kV line	Mitigated by generation adjustments
2	Engadine, Newberry, Newberry Hospital, Roberts, LouPac, Newberry Village 69-kV buses	--	--	--	89.1 – 89.6%	--	--	--	--	Hiawatha – Engadine 69-kV line ⁶	Mitigated by generation adjustments
2	Brevort, Hiawatha and Lakehead 138-kV buses	--	--	--	91.2 – 91.4%	--	--	--	--	Brevort – Straits 138-kV line	Targeted for mitigation by Eastern U.P. area reinforcements
2	Brevort and Lakehead 138-kV buses	--	--	--	91.6 – 91.7%	--	--	--	--	Brevort – Lakehead 138-kV line	Targeted for mitigation by Eastern U.P. area reinforcements
2	Hiawatha 138-kV bus	--	--	--	91.4%	--	--	--	--	Hiawatha – Lakehead 138-kV line	Targeted for mitigation by Eastern U.P. area reinforcements
2	North Bluff, Bay View, Mead, Gladstone, Masonville and Lakehead 69-kV buses	--	90.8 – 91.6%	--	--	--	--	--	--	Chandler 138/69-kV transformer	Mitigated by generation adjustments
2	Chandler, Delta, Escanaba, Masonville, Mead, Gladstone, West, Lakehead, North Bluff, Bay View, Cornell, Harris 69-kV buses	--	--	--	--	--	88.4 – 91.1%	--	--	Chandler 138/69-kV transformer	Mitigated by generation adjustments
2	Ontonagon, Stone Container and Winona 138-kV buses	--	91.3 – 91.7%	--	--	--	91.5 – 91.9%	--	--	M38 – Winona 138-kV line	Mitigated by generation adjustments
2	Straits, St. Ignace, Indian Lake, Evergreen, Valley, Glen Jenks, Manistique, Engadine, Hiawatha, Gould City, Curtis, Rexton, and Blaney Park 69-kV buses and Straits 138-kV bus	--	104.1 – 105.7%	--	--	--	104.2 – 108.0%	--	104.6 – 106.2%	System Intact	Adjust transformer tap settings at Hiawatha, Indian Lake, Straits
2	Hiawatha and Lakehead 138-kV buses	--	--	--	94.2 – 95.2%	--	--	--	105.9 – 106.0%	System Intact	Mitigated by generation adjustments
2	Alger Delta Hiawatha, Sault, Eckerman, Goetzville, Pickford, Rudyard, Newberry Hospital, Newberry Village, Three Mile, Magazine, Kinchloe, Trout Lake, Munising, Alger, Hulbert, Brimley, Dafter, Detour, Engadine, Newberry, Raco, LouPac, Roberts, ESE Hydro, Nine Mile, Pine River, Rockview, Pine Grove, Tone, Talentino 69-kV buses and Brevort 138-kV bus	--	--	--	--	--	--	--	105.0 – 106.5%	System Intact	Mitigated by generation adjustments
2	Lakota Road 69-kV bus	--	--	--	--	--	--	--	119.1%	Lakota Road – Conover 69-kV line	Resolved by transformer model adjustments
2	Lakota Road 115-kV bus	--	--	--	--	--	--	--	110.4%	Eagle River – Cranberry 115-kV line	Mitigated by generation adjustments
2	Atlantic 138-kV bus	--	--	--	--	--	--	--	113.0%	Atlantic – M38 138-kV line	Mitigated by generation adjustments
3	Base Case Loading Criteria Exceeded	FALSE	--	FALSE	--	FALSE	--	FALSE	--	System Intact	
3	Base Case Voltage Criteria Exceeded	--	FALSE	--	FALSE	--	FALSE	--	FALSE	System Intact	

Table ZS-1
2011 Limitations and Performance Criteria Exceeded

Planning Zone	Criteria Exceeded/Need	2011 Summer Peak Case		2011 90% Load Case		2011 70% Load Case		2011 Minimum Load Case		Facility Outage(s)	Project/Mitigation
		% of Facility Rating	% of Nominal Bus Voltage	% of Facility Rating	% of Nominal Bus Voltage	% of Facility Rating	% of Nominal Bus Voltage	% of Facility Rating	% of Nominal Bus Voltage		
3	Concord 138-kV bus	--	95.5%	--	--	--	--	--	--	System Intact	Mitigated by generation adjustments
3	Concord, Butler Ridge, and Rubicon 138-kV buses	--	--	--	95.2 – 95.9%	--	--	--	--	System Intact	Mitigated by generation adjustments
3	Butler Ridge and Rubicon 138-kV buses	--	90.9 – 91.4%	--	--	--	--	--	--	Hartford – St. Lawrence 138-kV line	Mitigated by generation adjustments
3	Crawfish River 138-kV bus	--	--	--	91.1%	--	--	--	--	Jefferson – Crawfish River 138-kV line	Mitigated by generation adjustments
3	Crawfish River and Concord 138-kV buses	--	90.5 – 91.7%	--	--	--	--	--	--	Jefferson – Crawfish River 138-kV line	Mitigated by generation adjustments
3	Paddock – Townline 138kV line	--	--	--	--	99.0% 97.1%	--	--	--	NW Beloit – Paddock 138-kV line Blackhawk – NW Beloit 138kV	Mitigated by generation adjustments
3	Hubbard and Hustisford 138-kV buses	--	96% 86.5% 87.1% 87.1% 90.7 – 90.9%	--	95.9% 87.2% 87.7% 87.7% --	--	-- 87.2% 87.3% --	--	--	System Intact Rubicon – Hustisford 138-kV line Hustisford – Hubbard 138-kV line Rubicon – Hustisford – Hubbard 138-kV line Hartford – St. Lawrence 138-kV line	Adjust Hubbard 138/69-kV transformer LTC
3	Fox Lake, North Beaver Dam and Beaver Dam East 138-kV buses	--	89.2 – 89.3%	--	--	--	--	--	--	North Randolph – Fox Lake 138-kV line	Adjust North Beaver Dam 138/69-kV transformer LTC
3	Fitchburg 138-kV bus	--	--	--	--	--	96.0%	--	--	System Intact	Femrite and Kegonsa 138-kV capacitor banks
3	Huiskamp 138-kV bus	--	--	--	88.6%	--	88.4%	--	--	Huiskamp – North Madison 138-kV line	Adjust Huiskamp 138/69-kV transformer LTC
3	Verona and Fitchburg 138-kV buses	--	--	--	--	--	91.8 – 91.9%	--	--	Columbia generator #1	Femrite and Kegonsa 138-kV capacitor banks
3	Nelson Dewey 161/138-kV transformer	--	--	--	--	95.6% 95.4%	--	--	--	CE Byron generator #1 CE Byron generator #2	Mitigated by generation adjustments
3	Nelson Dewey – Cassville 161-kV line	--	--	--	--	99.6% 95.8%	--	--	--	DPC Genoa generator #3 Columbia generator #2	DPC line limitation / further study needed
3	Fitchburg – Syene 69-kV line	104.9%	--	95.3%	--	--	--	--	--	Royster – AGA Tap 69-kV line	Short term Operating Guide / Nine Springs, Pflaum area project
3	Royster – AGA Gas Tap 69-kV line	103.0%	--	--	--	--	--	--	--	Fitchburg – Syene 69-kV line	Short term Operating Guide / Nine Springs, Pflaum area project
3	Verona 138-kV bus	--	95.7% 90.2%	--	-- 90.2%	--	--	--	114.8%	System Intact Verona – Oak Ridge 138-kV line	Adjust Verona 138/69-kV transformer LTC / Verona 69-kV capacitor bank project
3	Fitchburg, Cross County, Oak Ridge and Pleasant View 138-kV buses	--	95.3 – 95.9%	--	--	--	--	--	--	System Intact	Femrite and Kegonsa 138-kV capacitor banks
3	Verona, Oak Ridge, Pleasant View, Cross County, Pleasant View, and Fitchburg 138-kV buses	--	--	--	95.0 – 95.9%	--	--	--	--	System Intact	Femrite and Kegonsa 138-kV capacitor banks
3	REC Harmony, Milton Tap and Milton 69-kV buses	--	91.9 – 92.0%	--	--	--	--	--	--	McCue – Harmony 69-kV line	Lamar 69-kV capacitor bank project
4	Base case loading criteria exceeded	FALSE	--	FALSE	--	FALSE	--	FALSE	--	System Intact	
4	Base case voltage criteria exceeded	--	TRUE	--	FALSE	--	FALSE	--	TRUE	System Intact	
4	Badger & Belle Plaine 115-kV buses	--	105.0%	--	--	--	--	--	106.4%	System Intact	Switch Badger 138-kV capacitor banks offline
4	East Krok 138/69-kV transformer	103.2%	--	103.1%	--	98.1%	--	--	--	Canal – East Krok 138-kV line	No project needed Investigation into limiting facility resulted in higher facility ratings
4	Sunset Point – Pearl Avenue 69-kV line	108.2% 107.8%	--	97.1% 97.0%	--	--	--	--	--	Ellinwood 138/69-kV transformer ³ Ellinwood – 12th Avenue 69-kV line	Rebuild line
4	Morgan – Falls 138-kV line	--	--	--	--	105.7%	--	--	--	Morgan – Plains 345-kV line	Mitigated by generation adjustments
4	White Clay 138-kV 1-2 bus tie	--	--	--	--	96.0%	--	--	--	Morgan – Highway 22 345-kV line	Further study needed
4	North Appleton, Apple Hills, Maes, Combined Locks tap & City Limits 138-kV buses	--	--	--	--	--	--	--	104.1 – 105.3%	System Intact	Switch off area capacitor banks

Table ZS-1
2011 Limitations and Performance Criteria Exceeded

Planning Zone	Criteria Exceeded/Need	2011 Summer Peak Case		2011 90% Load Case		2011 70% Load Case		2011 Minimum Load Case		Facility Outage(s)	Project/Mitigation
		% of Facility Rating	% of Nominal Bus Voltage	% of Facility Rating	% of Nominal Bus Voltage	% of Facility Rating	% of Nominal Bus Voltage	% of Facility Rating	% of Nominal Bus Voltage		
4	Werner West, Werner & Hintz 138-kV buses	--	--	--	--	--	--	--	105.4 – 105.5%	System Intact	Switch off area capacitor banks
4	City Limits, Lake Park & Forest Junction 138-kV buses	--	--	--	--	--	--	--	104.1 – 105.1%	System Intact	Switch off area capacitor banks
4	Butte des Morts, Northside, Tayco, Melissa, Meadows Kaukauna Central tap & Forest Junction 138-kV buses	--	--	--	--	--	--	--	104.2 – 105.1%	System Intact	Switch off area capacitor banks
4	Kaukauna Central tap, Kaukauna Central, Kaukauna North & North Appleton 138-kV buses	--	--	--	--	--	--	--	104.9 – 105.3%	System Intact	Switch off area capacitor banks
4	Glenview 138-kV bus	--	--	--	--	--	--	--	105.1%	System Intact	Switch off area capacitor banks
5	Base Case Loading Criteria Exceeded	FALSE	--	FALSE	--	FALSE	--	FALSE	--	System Intact	
5	Base Case Voltage Criteria Exceeded	--	TRUE	--	TRUE	--	FALSE	--	TRUE	System Intact	
5	Bluemound 230-kV bus, Allerton, Bark River, Brookdale, Cooney, Cottonwood, Germantown, Hartford, Maple and Summit 138-kV buses	--	94.5 – 96.0%	--	--	--	--	--	--	System Intact	Mitigated by generation adjustments
5	Bluemound 230-kV bus, Bark River, Cooney, Cottonwood, Germantown, Hartford, Mukwonago, Maple and Summit 138-kV buses	--	--	--	94.5 – 95.9%	--	--	--	--	System Intact	Mitigated by generation adjustments
5	Montana, Barland, Valley, Racine, Dewey, Albers, Allerton, Branch, Center, Everett, Fiebrantz, Hayes, Harbor, Haymarket, Kansas, Kenosha, Lincoln, Nicholson, Norwich, Oak Creek, Parkhill, Pennsylvania, Racine, Ramsey, St. Rita, 28th St, and Somers 138-kV buses	--	--	--	--	--	--	--	105.0 – 105.8%	System Intact	Mitigated by generation adjustments
5	Germantown 138-kV bus	--	91.3%	--	--	--	--	--	--	Germantown – Maple 138-kV line	Mitigated by generation adjustments
5	Bark River and Germantown 138-kV buses	--	91.6 – 91.7%	--	--	--	--	--	--	Bark River – Sussex 138-kV line	Mitigated by generation adjustments
5	Bark River, Cottonwood and Germantown 138-kV buses	--	--	--	91.5 – 91.9%	--	--	--	--	Bark River – Sussex 138-kV line	Mitigated by generation adjustments
5	Hartford 138-kV bus	--	90.4%	--	91.9%	--	--	--	--	Hartford – St. Lawrence 138-kV line	Mitigated by generation adjustments
5	Maple, Germantown, Bark River, and Cottonwood 138-kV buses	--	85.8 – 91.6%	--	--	--	--	--	--	Maple – Saukville 138-kV line	Mitigated by generation adjustments
5	Maple and Germantown 138-kV buses	--	--	--	88.7 – 89.1%	--	--	--	--	Maple – Saukville 138-kV line	Mitigated by generation adjustments
5	Bain 345/138-kV transformer #5	159.5% 113.6%	--	159.2% --	--	146.9% --	--	146% --	--	Split Pleasant Prairie 345-kV bus 34 Split Pleasant Prairie 345-kV bus 23	Mitigated by generation adjustments
5	Oak Creek 345/230-kV transformer T895	104.7% 103.4%	--	104.7% --	--	-- --	--	-- --	--	Split Oak Creek 230-kV bus 78 Split Oak Creek 230-kV bus 67	Mitigated by generation adjustments
5	Arcadian4 – Waukesha1 138-kV line	107.1%	--	131.1%	--	115.0%	--	--	--	Arcadian6 – Waukesha3 138-kV line	Rebuild line
5	Arcadian6 – Waukesha3 138-kV line	110.8%	--	126.7% 111.3%	--	111.2% 99.8%	--	--	--	Arcadian4 – Waukesha1 138-kV line Split Waukesha 138-kV bus 12	Rebuild line
5	Arcadian 345/138-kV transformer #3	101.5%	--	109.9% 105.8%	--	100.3%	--	--	--	Arcadian 345/138-kV transformer #1 Split Arcadian 345-kV bus 12	Replace transformer
5	Arcadian 345/138-kV transformer #2	--	--	101.8% 97.5%	--	--	--	--	--	Arcadian 345/138-kV transformer #1 Split Arcadian 345-kV bus 12	Replace transformer
5	Albers – Kenosha 138-kV line	--	--	102.5%	--	116.0%	--	--	--	Albers – Bain 138-kV line	Mitigated by generation adjustments
5	Waukesha 138-kV bus 12	--	--	98.2%	--	--	--	--	--	Arcadian6 – Waukesha3 138-kV line	Mitigated by generation adjustments
5	Harbor – Kansas 138-kV line	--	--	102.1% 97.4% 97.3% -- --	--	108.7% 99.4% 106.3% 106.4% 105.4% 102.4%	--	--	--	Kansas – Norwich 138-kV line Harbor – Norwich 138-kV line Split Dewey 138-kV bus Dewey – Norwich 138-kV line Montana – Dewey 138-kV line Montana – Valley 138-kV line	Mitigated by generation adjustments
5	Granville – Rangeline 138-kV line	--	--	101.2%	--	--	--	--	--	Cornell – Granville 138-kV line	Mitigated by generation adjustments

Table ZS-1
2011 Limitations and Performance Criteria Exceeded

Planning Zone	Criteria Exceeded/Need	2011 Summer Peak Case		2011 90% Load Case		2011 70% Load Case		2011 Minimum Load Case		Facility Outage(s)	Project/Mitigation
		% of Facility Rating	% of Nominal Bus Voltage	% of Facility Rating	% of Nominal Bus Voltage	% of Facility Rating	% of Nominal Bus Voltage	% of Facility Rating	% of Nominal Bus Voltage		
5	Oak Creek – Ramsey 138-kV line	--	--	102.1% 101.3% 100.5% 100.0% 97.4%	--	--	--	--	--	Valley generator #1 Edgewater generator #5 Oak Creek – Pennsylvania 138-kV line Edgewater generator #4 System Intact	Mitigated by generation adjustments
5	Edgewood – St. Martins 138-kV line	--	--	--	--	99.9%	--	--	--	Merrill Hills – Waukesha 138-kV line	Mitigated by generation adjustments

Table ZS-1_2011 constraints

Definition of Event Based Contingencies to be included in Appendix:	
1	Arpin - Rocky Run 345-kV line + Port Edwards - Sand Lake 138-kV line + Port Edwards - Hollywood 138-kV line + Council Creek - Council Creek DPC 69-kV line
2	Dead River 345/138-kV xfmr #1 and Dead River 345/138-kV xfmr 1A
3	Ellinwood 138/69 kV xfmr #1 + Ellinwood - Twelfth Ave 69 kV circuit + Ellinwood - Fitzgerald 138 kV circuit + Ellinwood 138 kV bus tie 1-2
4	Whitcomb - CWEC Wittenberg Tap - Wittenberg Tap - Birnamwood Tap - Brooks Corner - Deer Trail 69-kV line
5	M38 – Atlantic 138-kV line + Atlantic 138/69-kV transformer
6	Hiawatha-Engadine 69-kV line + Hiawatha 138/69-kV transformer